

NOVO LCD Co.

No	Symbol	Description	Remarks
1	GND	Ground	
2	VCC	Power Supply,3.3V(typical)	
3	VCC	Power Supply,3.3V(typical)	
4	V_EDID	EDID 3.3V power	
5	ADJ	Adjust the Back Light brightness(Note1,2)	
6	CLK_EDID	EDID Clock	
7	DATA_EDID	EDID Data	
8	Rin0-	- LVDS differential data input(R0-R5,G0)	
9	Rin0+	+ LVDS differential data input(R0-R5,G0)	
10	GND	Ground	
11	Rin1-	- LVDS differential data input(G1-G5,B0-B1)	
12	Rin1+	+ LVDS differential data input(G1-G5,B0-B1)	
13	GND	Ground	
14	Rin2-	- LVDS differential data input(B2-B5,HS,VS,DE)	
15	Rin2+	+LVDS differential data input(B2-B5,HS,VS,DE)	
16	GND	Ground	
17	ClKIN-	-LVDS differential clock input	
18	ClKIN+	+LVDS differential clock input	
19	GND	Ground	
20	NC	No Connection(Reserve)	
21	NC	No Connection(Reserve)	
22	GND	Ground	
23	GND	Ground	
24	VLED	LED Power Supply 5V	
25	VLED	LED Power Supply 5V	
26	VLED	LED Power Supply 5V	
27	NC	No Connection(Reserve)	
28	NC	No Connection(Reserve)	
29	NC	No Connection(Reserve)	
30	NC	No Connection(Reserve)	

NOVO LCD Co.